

Wemos MINI Shield Pinassignment list

<https://www.b4x.com/android/forum/threads/arduino-to-wemos-pin-mapping.76394/>

		D0	D1	D2	D3	D4	D5	D6	D7	D8
Arduino ==>		GPIO16	GPIO5	GPIO4	GPIO0	GPIO2	GPIO14	GPIO12	GPIO13	GPIO15
Special function ==>		10k pullup	SLC	SDA		buildinLED 10k up	SCK	MISO	MOSI	SS
OLED	Display		SLC	SDA						
Relay	0-230V switch		Output							
MicroSD							SCK	MISO	MOSI	SS
Motor	2x max 15V 3A		SLC	SDA						
DHT pro	Temp+Hum					OneWire				
DHT	Temp+Hum					OneWire				
DS18B20	Temp			OneWire						
SHT30	Temp+Hum		SLC	SDA						
WS2812B	RGB prog led			OneWire						
BMP180	Pressure		SLC	SDA						
1-Button	pushbutton				Input					
Matrix LED 8x8							CLK		DIN	
Buzzer							ON/OFF	optie	optie	optie

