

Bill of Materials for PCB-based IV Swinger 2

PV type Relay
Type Type

PV cell EMR

Description	Quantity	Name(s)	Unit Price	Total Price	Purchase From	Notes
On-PCB parts						
10-pin stackable female header	1	A1				Purchased as a kit of all four. Note, however, that A4 is not needed at all, and A1 can be 8-pin instead of 10-pin (pins 9 and 10 are not used). Digi-Key PN: 1568-1413-ND
8-pin stackable female header	2	A2, A3	\$1.50	\$1.50	Digi-Key	
6-pin stackable female header	0	A4				
2200µF 6.3V capacitors	2	C1, C2	\$2.55	\$5.10	Digi-Key	Digi-Key PN: 493-12454-ND
0.1µF capacitor	2	C3, C6	\$0.26	\$0.52	Digi-Key	Op amp and ADC Vdd filter. Digi-Key PN: BC2665CT-ND
2.2nF (2200 pF) capacitor	2	C4, C5	\$0.38	\$0.76	Digi-Key	Voltmeter and ammeter op amp circuits. Digi-Key PN: 399-4166-ND
4-pin female header	1	FH	\$0.47	\$0.47	Digi-Key	Extra +5V and GND for temperature and irradiance sensors. Can be omitted if no plans for those (or can be added later). Digi-Key PN: S7037-ND
2-pin screw-terminal block	2	J1, J2	\$0.99	\$1.98	Digi-Key	Digi-Key PN: A97996-ND
8-pin DIP socket (optional)	2	MCP3202, TLV2462	\$0.45	\$0.90	Digi-Key	IC sockets. Recommended so ICs can be replaced more easily. Digi-Key PN: 1212-1003-ND
ADC - MCP3202	1	MCP3202	\$3.77	\$3.77	Digi-Key	Digi-Key PN: MCP3202-BI/P-ND
Op amp - TLV2462	1	TLV2462	\$2.82	\$2.82	Digi-Key	Ammeter. Digi-Key PN: 296-1892-5-ND
Not present in cell version	0	R1	\$0.01	\$0.00	Amazon	Voltmeter - divider
Not present in cell version	0	R2	\$0.01	\$0.00	Amazon	Voltmeter - divider
1kΩ resistor - 1/4W	3	R3, R4, R6	\$0.01	\$0.02	Amazon	Voltmeter and ammeter op amp circuits, relay input
22kΩ resistor - 1/4W	3	R5,R6,R7	\$0.01	\$0.02	Amazon	Arduino output pull-ups
Not present in EMR version	0	R7-R11	\$0.01	\$0.00	Amazon	SSR pull up/downs
75kΩ resistor - 1/4W	1	RF	\$0.01	\$0.01	Amazon	Ammeter - op amp circuit
680kΩ resistor - 1/4W	1	RF1	\$0.01	\$0.01	Amazon	Ammeter - op amp circuit
Not present in cell version	0	RB	\$0.78	\$0.00	Digi-Key	Bleed resistor. Needs to be able to handle 6.4J pulse energy (for 80V Voc; less for lower Voc: 0.5 * 0.002F * Voc^2). Digi-Key PN:PPC5W47.0CT-ND
0.005Ω shunt resistor	1	SHUNT	\$3.04	\$3.04	Digi-Key	Ammeter. Digi-Key PN: 13FR005E-ND
2-pin header	1	JP	\$0.13	\$0.13	Digi-Key	Low current jumper header. Digi-Key PN: 732-5315-ND
2-pin jumper	1	JP	\$0.10	\$0.10	Digi-Key	Low current jumper. Digi-Key PN: S9337-ND
x1 DIP switch	1	OFF=LO_CUR	\$0.91	\$0.91	Digi-Key	Alternate to jumper. Digi-Key PN: 732-3831-5-ND
Not present in EMR or FET version	0	SSR1-SSR6	\$7.00	\$0.00	Digi-Key	Solid State Relays (SSRs). Digi-Key PN: CLA315-ND
Not present in EMR or SSR version	0	FET1, FET2, FET3	\$1.23	\$0.00	Digi-Key	Field Effect Transistors (FETs). Digi-Key PN:IRF540NPBF-ND
Not present in EMR or SSR version	0	CPC1596	\$2.78	\$0.00	Digi-Key	Gate driver for FET1. Digi-Key PN:212-CPC1596G-ND
15SQ045 Schottky bypass diode(45V)	1	D1,D2	\$0.80	\$0.80	Digi-Key	Reverse connection bypass diode. Connect between pads D1 and D2. Digi-Key PN: 1655-1354-1-ND
Off-PCB parts						
Arduino Uno clone	1	Arduino	\$14.99	\$14.99	Amazon	Elegoo UNO R3 Board ATmega328P ATMEGA16U2 with USB Cable Compatible With Arduino UNO R3
Donation to arduino.cc	1	Donation	\$5.00	\$5.00	arduino.cc	
Binding posts	2	Binding posts	\$4.09	\$8.18	Digi-Key	Digi-Key PN: 501-1713-ND
2-channel relay module, active low trigger	1	EMR	\$6.79	\$6.79	Amazon	SunFounder 2 Channel DC 5V Relay Module with Optocoupler Low Level Trigger Expansion Board for Arduino UNO R3 MEGA 2560 1280 DSP ARM PIC AVR STM32 Raspberry Pi
18ga solid wire or zip cord	1	Load circuit wire	\$2.94	\$2.94	Amazon	For load circuit wires: MC-4 to binding posts, binding posts to relay/PCB, relay to PCB. Scrap appliance cord is fine. Just want a heavier duty than hookup wire.
Cable ring connectors	5	Cable rings	\$0.21	\$1.05	Digi-Key	Binding post internal connections. Digi-Key PN: 277-11154-ND
4 inch Male to Female jumpers (1 blue, 1 white, 1 red, 1 black)	4	Jumpers	\$0.07	\$0.30	Amazon	Relay to stack connector wires. GenBasic 80 Piece Male to Female Solderless Ribbon Dupont Jumper Wires (4 and 8 Inch) for Breadboard Prototyping
Enclosure						
Ultra Pro Baseball Clear Square Holder	1	Case	\$5.99	\$5.99	Amazon	Price goes up in baseball season
M3 15mm body, 6mm thread nylon male-female standoff spacer	8	Standoffs	\$0.24	\$1.90	Amazon	uxcell 50pcs M3 15+6mm Male Female Thread Nylon Hex Standoff Spacer Screws PCB Pillar Black (also available from Digi-Key or eBay)
M3 screws (1/4 inch)	8	Screws	\$0.07	\$0.53	Amazon	StarTech PC Mounting Computer Screws M3 x 1/4-Inches Long Standoff - 50 Pack SCREWM3 (also available from Digi-Key or eBay)
M3 nuts	8	Nuts	\$0.06	\$0.50	Amazon	Shapenty 100PCS 3mm Small Stainless Steel Female Thread Hex Screw Nut Fastener Tool, M3 (also available from Digi-Key or eBay)
Not needed for cell version	0	MC-4	\$4.99	\$0.00	Amazon	JYFT Solar Panel Cable Connectors Male/Female IP67 30A 1000V DC (1Pair)
Bias Battery						
D-cell battery holders	2		\$3.14	\$6.28	Digi-Key	Digi-Key PN: BH2DL-ND
4-pack of D-cells	1		\$7.98	\$7.98	Amazon	Or at grocery store, Target, etc.
Total				\$71.03		

Amazon wish list: <http://a.co/aBTNpST>

Digi-Key cart: <https://www.digikey.com/short/7d09z2nm>

Digi-Key/Mouser CSV: https://raw.githubusercontent.com/csatt/IV_Swinger/master/PCB/BOM/DigiKeyMouser/emr_cell_DigiKey_Mouser.csv

Only purchase items with ALT_# in Customer Reference if primary has Availability = "Backorder"